

此 PDF 文档中显示的数据是由我们的在线目录生成的，仅供参考，请以实际产品说明书为准。

### **GS8247-EX.AM AI,Isolated Barrier(1 channel)**

This product Input signal 4~20mA,Output signal 4~20mA RS485.provide isolated supplies for transmitter which located in hazardous area. at the same time, provide one channel of RS-485 bus output which based on MODBUS-RTU protocol and two channels of relay alarm output.power supply and RS-485 can be connected with rail,Power connecting mode DIN Rail BUS or Terminal.



Number of channels: 1input/2output

Input signal: 4~20mA

Power Distribution: 15.5V/20mA

Analogue Output: 4~20mA

RS-485 Output: Involve

Power Connection Mode: Terminal Power Supply ,Bus Power Supply

## 产品参数

**上海辰竹仪表有限公司**  
SHANGHAI CHENZHU INSTRUMENT CO.,LTD.

**如需更多信息，请与辰竹联系 For more information, please contact:**

销售服务 Sale service: 021-64360668

邮箱 Mail: [chenzhu@chenzhu-inst.com](mailto:chenzhu@chenzhu-inst.com)

技术支持 Tech service: 400 881 0780

网址 Web: [www.chenzhu-inst.com](http://www.chenzhu-inst.com)